

Page system

Some customers may experience problems with album pages on series 3-4 systems. This is due to the excess weight these pages are carrying i.e. Album booklets as opposed to album covers

The voltage source for the page motor needs increasing from +5V DC to +7.4V DC, this is achieved by inserting a zener diode (Z1 2.4V) into the centre leg of voltage regulator VR 1. This voltage regulator is located as follows.

Free standing juke boxes:- On the wall box distribution board

Wall Boxes:- On the wall box interface board

